Send Programs

ogram		Machine Table				Record	12 of 14	
'olling 🗾	1	Detail Comm	Programs RJE Timir	ng				
🎲 Machine List		Machine ID	Sharp 810	Stor	re Sharp, 1		•	
Casio 4500		Program ID	sharp_810	Comm Typ	e TCP/IP		-	
Casio 6600		Machine #	1		Number o	of Satellites None	Allocated	
Casio 6600 II								
Sam 2000		Mfg S	Sharp	ROM Versio	on 1.30	2600 -		
Sam 520		Model Jo		Baud Rat		9800		
Sam 520 test		• • • •	₩ ₩ + - </td <td>× 🛷 🗶 🛛 👔</td> <td>🖇 🛤 🖴</td> <td>🖗 🔦 🛛 Sear</td> <td>ch 🛛</td> <td></td>	× 🛷 🗶 🛛 👔	🖇 🛤 🖴	🖗 🔦 🛛 Sear	ch 🛛	
Sam 7000	*	MachineId Casio 4500	ProgramId casio_4500	StoreNum Ma	chineN 25			
Sharp 3500		Casio 6600 Casio 6600 II	casio_6600 casio_6600	1	1			
Sharp 600		Sam 2000 Sam 520	Sam_2000 Sam 520	1	1			
Sharp 700		Sam 520 test Sam 7000	sam_520_test	7	45			
Sharp 700 test		Sharp 3500 Sharp 600	sharp_3500	1	1			
Sharp 810 🔳		Sharp 700	sharp_700	1	20			
🔀 Communications	╢┝	Sharp 810	sharp 810	1	1			
🐊 Maintain		Tec 1595	tec_1595	39	1			
	11-	Tec 1650	tec_1650	1	1			
👅 Setup								
Setup Preferences	-111							
Setup Setup Preferences								

1. To send programs within the V7 Polling software, pick the register by going to **Machine List** on the left menu. Click on the register which in this example is the Sharp 810.

PC Poll V7							×
Program Poling Machine List Communications Communicate Run Script Run Schedule Comm History	Select	t Machines / Pro	ıgrams	rebe	Vhen Communio only allowed to Sand or Poll Re gister. Multiple conducted by	cating, you select eith re, ports for ea selections creating sc	are her may ripts
Setup Preferences							
Reports Most Recent	🔀 Begin	? Help	Clear All			-	
Machine ID: Sharp 81	0	Program ID: s	harp_810		🗐 Close	👖 Exit	7 <u>H</u> elp

- 2. Click on **Communications** on the menu on the left, then **Communicate**.
- 3. Click on the plus sign [■] in front of the appropriate register which in this example is the Sharp 810.



- 4. In figure A, click the plus sign in front of **Send Programs to Register** to open the list of programs that can be sent from the register.
- 5. In figure B. to check off all of the programs at one time, click on **All Programs**. To remove all the check marks, click on **All Programs** again. The programs can also be selected one at a time.



6. By clicking the plus signs in front of **Department** and **PLU/UPC**, additional programs will be available.

Note: Some programs are not automatically selected by the **All Programs** option. Specific programs have been excluded as edits to them can change general communications settings. Please consult a cash register dealer for more information on those programs and how edits to them will affect the cash registers.

- 7. When done selecting the programs to send, click the **Begin** button.
- 8. The **Help ?** Help button opens the Help Files.

PC Poll V7 Eile Tools Help			IX
Program	Select Machines / Programs		
Polling	Casio 4500		
🖓 Machine List	≝ Casio 6600 ≝ Casio 6600 II		
S Communications	≝⊷∐ Sam 2000 ₩-□ Sam 520		
Communicate	■ □ Sam 520 test ■ □ Sam 7000	When Communicating, you are	
Run Script		only allowed to select either Save,	
Run Schedule	In an p 700 In International P 700 test	Send or Poll Reports for each	
Comm History	≝ ☐ Sharp 810 ≝ ☐ Tec 1595	be conducted by creating scripts	
💝 Maintain			
Setup			
1 Reports			
Most Recent	Begin 7 Help Clear All		
Machine ID: Sharp 81	0 Program ID: sharp_810	📕 Close 👖 Exit 🦿 Help	

- 9. The **Clear All** button un-checks all selections on the Select Machine/Programs screen. And returns the screen to the above.
- 10. To close the screen, click the **Close** button at the bottom of the screen.
- 11. To exit the program, click **Exit** at the bottom of the screen.